




DWRX/XXW/830/120DT
DWRX/XXW/9CCT5/120DT



INSTALLATION INSTRUCTIONS LED Downlight Wafer Remote Driver

SAFETY PRECAUTIONS:

- READ ALL INSTRUCTIONS BEFORE INSTALLING FIXTURE, RETAIN FOR FUTURE REFERENCE.
- IMPORTANT: This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
- WARNING: For your safety, this fixture must be wired in accordance to local electrical codes and ordinances.
- WARNING: All work should be done by a qualified electrician.
- WARNING: Make certain power is OFF from the electrical panel before starting installation or attempting any maintenance.
- INDOOR INSTALLATION ONLY.

INSTALLATION:

ALWAYS TURN OFF THE POWER SUPPLY FROM MAIN CIRCUIT BREAKER FIRST!

1. Open the hardwire box swing cover and remove the appropriate knockout(s).
2. Insert the electrical supply cable through knockout and secure with a cable connector (sold separately).
3. Using connection terminal, connect green ground wire of cable to green wire on box.
4. Connect white wire of cable to white wire of box.
5. Connect black wire of cable to black wire of box. (Figure 1)
6. Place all wiring and connections back into the box and close the cover.
7. Insert hardwire box through the mounting hole. (Figure 2)

New Construction Applications: Hardwire box shall be firmly secured to studs, joists, or similar fixed structural units.

Remodel Applications: Hardwire box shall be firmly secured to studs, joists, or similar fixed structural units.

8. Make two holes in the wall, the spacing of the two holes is 1.6". Fix the hardwire box with screws. (Figure 3)
9. Connect the fixture to the hardwire box by inserting and twisting the male/female connectors. (Figure 4)
10. Push spring loaded clips on the fixture upwards and insert fixture base in to the mounting hole.
11. Release the clips and fixture will be pulled flush to the ceiling. (Figure 5)
12. Once assembly is complete, turn on power to confirm fixture is working properly.

