

Slim Emergency Exit Sign Combo

ESC02 Series



Illumination

- Adjustable long lasting, efficient ultra-bright white LED lamp heads.
- •2 X 1W white LED per lamp head.180 lumen output.
- Unique all inclusive lamp, reflector and lens assembly.
- Long-lasting, energy efficient Red or Green LED exit sign illumination.

Electrical

- 120V-277VAC universal input voltage.
- Test switch and charge indicator.
- Built-in 3.6V 1000mAH long-life, maintenance-free, rechargeable
- Ni-Mh battery for standard models. 3.6V 2000mAH long-life, maintenance-free, rechargeable Ni-Mh battery for models with remote heads.
- Internal solid-state transfer switch automatically connects the internal battery to LED board for minimum 90-minute emergency illumination.
- Fully automatic solid-state, two rate charger initiates battery charging to recharge a discharged battery in 24 hours.

DOE CULUS ROHS CEC FC

ı	Project Detail	Туре	
	Project:		
	Product:		
	Prepared by:		
	Notes:		

Mounting

- EZ-snap mounting canopy included for top or end mount.
- Universal J-Box mounting pattern.

Housing

- Injection-molded thermoplastic ABS and PC housing.
- UL 94v-0 flame rating.
- White or Black finish. SALIDA faceplate available.


Options

- Remote capacity option available.
- Remote load capability is up to 2W, compatible with two 1-lamp remote heads or one 2-lamp remote head (RH01 Series).
- Single or double face (Universal). *SALIDA faceplate available.
- *One faceplate pre-installed.The other one comes as optional in the packing.

Warranty/Listing

- Five year warranty on all electronics and housing. Batteries 3 years.
- Meets UL924.
- UL listed for damp locations (0° -40°C)





2.04" (52mm)

Order Format							Example : ESC02-G1-WH	
Series		Letter Color	Letter Type		Voltage		Finish Color	Other Options
ESC02		G-Green	1=Exit		Blank=120-277V	-	WH=White	Blank
ESCUZ	- [R=Red*	2=Salida**	-			BL=Black**	RC=With Remote Load***

^{*} Red letter and white finish comes as default. Contact sales for extra lead time on green letter or black finish.

^{**} SALIDA faceplate comes as optional accessory.

^{***} Remote load comes as default.